

# Body Infrared Thermometer



## Body Infrared Thermometer

- ⦿ Non-contact measuring temperature accurately
- ⦿ It can reduce the risk of virus spread effectively
- ⦿ Reading temperature display quickly response time is only 0.5s
- ⦿ Accuracy is  $\pm 0.3^{\circ}\text{C}$  ( $\pm 0.6^{\circ}\text{F}$ )
- ⦿ 34 Measuring datas can be saved



NORMAL

SLIGHT

SERIOUS



READY STOCK

### Technical Parameters

Temperature Measuring Range	32~43°C (90-109°F)
Temperature Measuring Accuracy	$\pm 0.3^{\circ}\text{C}$ ( $\pm 0.6^{\circ}\text{F}$ )
Surface Temperature Measuring Range	0~100°C (32-212°F)
Surface Temperature Measuring Accuracy	$\pm 1^{\circ}\text{C}$ ( $\pm 1.8^{\circ}\text{F}$ )
Minimum Readings	$\pm 0.1^{\circ}\text{C}$ ( $\pm 0.1^{\circ}\text{F}$ )
Response Time	0.5s
Measuring Distance	5~8cm
Auto Power Off	7s



### Specification

Storage Temperature	-10~60°C (14-140°F)
Usage Temperature	10~40°C (50~104°F)
Usage Battery	3V
Weight	122g
Size	145 x 80 x 40mm